

# Using Slackware-current

**Note:** I have removed a section on DE-less installation since my current slackware installations ARE, in fact, DE-less.

**Note:** I have also removed a section on hijacking other Linux system - this, here, turned out to be VERY similar to what needed to be done.

## [LastUpdated20210620]

I need to use GTK3 version that is newer than the one on 14.2, so I tried the development version (**slackware64-current**). I have done the same once (pre-11), so I am aware that there can be some issues when doing this. I am happy to say that I AM writing this on a slackware64-current (15.0 beta?) installation on my laptop.

So, this is a little note to my future self (or anybody that may find this useful **DISCLAIMER: Use this at your own risk!**). I am doing this while still using Devuan and I want to keep that for backup, in case things go wrong. (On a side note, the reason I use Devuan was because of the GTK3 version.) So, I have an extra partition that I have reformatted and prepared to download the stuffs I need.

- download official packages (getslack)
  - create download path: <mount-path>/home/share/slackware
  - create custom getslack config .getslack
  - set VERS=current
  - exclude kde & xfce
- setup EFI boot
  - bzImage in kernels/huge.s (rename to vmlinuz)
  - initrd.img in isolinux/ (this has the slackware setup)
- boot and run installation as usual
  - DO NOT format partition (packages are there!)
  - pick packages from mounted path
  - manually set kernel to boot (i use huge - generic needs initramfs)
- boot newly installed slackware
  - remove gnuchess and xaos packages
  - make sure vim does not create backups (edit usr/share/vim/vimrc)
  - allow dmesg for user
    - append etc/rc.d/rc.local ← echo 0 > /proc/sys/kernel/dmesg\_restrict
  - just for personal reference, some useful info on using nmcli

```
nmcli r[adio] wifi
nmcli r[adio] wifi on

nmcli d[evice] wifi list
nmcli d[evice] wifi connect <ssid> password <pass> ifname <wlan0>

nmcli c[onnection] show
nmcli c[onnection] down <ssid>
nmcli c[onnection] up <ssid>
```

- customize etc/xdg/user-dirs.defaults (standard default paths)

- create user
- **things to note!**
  - elogind conflicts with my acpi scripts (lid, to be exact)
    - insert into etc/elogind/logind.conf ← HandleLidSwitch=ignore
  - pm-utils not available
    - use loginctl instead (e.g. loginctl suspend instead of pm-suspend)
    - on the plus side, does not need root

From:  
<http://azman.unimap.edu.my/dokuwiki/> - Azman @UniMAP

Permanent link:  
[http://azman.unimap.edu.my/dokuwiki/doku.php?id=linux:slack\\_1current&rev=1736588017](http://azman.unimap.edu.my/dokuwiki/doku.php?id=linux:slack_1current&rev=1736588017)

Last update: **2025/01/11 17:33**

