

General Notes

Miscellaneous...

SQ11 Info

Useful info on sq11 mini cam...

[sq11_info.txt](#)

Operating Instructions SQ11

Charging

Attention! Before using for the first time, fully charge the mini camera battery!

This mini video camera has a built-in lithium-ion battery. You can perform

charging in one of the following ways:

1. Connect the mini video camera to the USB port of your PC, stop recording first.
2. Connect the mini camera to a charger from a 220V network or a portable 5V charger. In this case, you can continue to use the mini-camera in the charging process. In the charging process, the blue and red LEDs will light constantly.

After the mini camera battery is fully charged, the blue LED will light constantly and the red LED will turn off.

- If the built-in battery is empty or there is not enough space on the memory card to continue, the blue and red LEDs on the mini camcorder will blink for 5 seconds simultaneously, after which the mini camcorder will save the recorded video and automatically turn off.
- If the memory card is not installed, the blue and red LEDs of the Mini Recorder will blink simultaneously for 5 seconds, after which the Mini Camera will automatically turn off.
- If the camcorder is in the standby mode and does not take any action

on it,

the camcorder automatically turns off after 1 minute to save the charge of the built-in battery.

Video recording

- Shooting video with a resolution of 1280X720P

Press the <On / Off> button to turn on the mini camera - the blue LED will light up - the mini camcorder is in the video recording standby mode with 720p quality. Press the <On / Off> button once to start recording video - the blue LED will blink 3 times and go out - 720p video is recorded. The video will be automatically saved every 5 minutes. To stop recording, press the <On / Off> button.

- Shooting video with a resolution of 1920X1080P

Press the <On / Off> button to turn on the mini camera - the blue LED will light constantly. Press the <Mode> button once to enter the video capture mode with 1080p resolution - the red and blue LEDs will light simultaneously, the mini camera is in the video recording standby mode with 1080p quality. To start recording, press the <On / Off> button once - the blue LED will go out, and the red LED will blink 3 times and go out - the video is recorded with a quality of 1080p. The video will be automatically saved every 5 minutes. To stop recording, press the <On / Off> button.

- Motion sensor video recording

To do this, while in the 720p or 1080p video recording standby mode, press and hold the <Mode> button of the mini video camera for 3 seconds - the camcorder enters the motion sensor recording mode. If motion is detected, the video recording will start automatically, with red and blue LEDs blinking at the same time. When recording motion sensor, the video recording is automatically saved every 5 minutes.

- Photo

Press the <On / Off> button to turn on the camera - the blue LED will

light up.

Press the <Mode> button twice to enter the photographing mode - the red LED will stay lit. To take a picture, press the <On / Off> button once - the red LED blinks once, the photo is saved. The resolution of the received photos is 4032x3024.

- Night light

Press the <On / Off> button to turn it on. Press and hold the <On / Off> button for 2 seconds - the red LED will blink twice - the night illumination is on. To turn off the night illumination, press and hold the <On / Off> button for 2 seconds, the red LED will blink three times - the night illumination is turned off.

- Shutdown

To turn off the camcorder, press and hold the <On / Off> button for 6 seconds.

If the Mini Camcorder is in the standby mode and is not in use, it automatically turns off after 1 minute.

- Viewing files

Do connect the camcorder in the off state to the computer - after a few seconds it will automatically be detected as a removable disk. The blue indicator will indicate the transfer of information, and the red indicator will indicate the charging of the built-in battery.

Parameters

- Video resolution: 1920x1080, 1280x720
- Frame rate: 15, 30 frames per second
- Video file type: AVI
- Photo resolution: 4032x3024
- Photo file type: JPEG
- Viewing angle: 140 °
- Night illumination: 6 IR LEDs (range of 5 meters, DO NOT emit light!)
- Motion sensor: Yes (range 5 meters)
- Recording while charging: +
- Duration of work:
 - > 100 minutes (1 hour 40 minutes) in constant recording mode
 - > About 5 hours in motion sensor mode
 - > 24/7 24/7 clock when external power is connected
- Support for memory cards: Micro SD up to 64GB
- Cyclic recording: +

- Operating temperature: $-10^{\circ}\text{C} + 60^{\circ}\text{C}$
- Humidity of the environment: 15-85%
- Dimensions: 23x23x23 mm, 15 grams

Mini camera SQ11 with night illumination, motion sensor and viewing angle 140°.

Mini DV SQ11 is an improved version of the previous SQ8 and SQ9

The camera SQ11 has a built-in motion sensor, can shoot photos with a resolution of 4032x3024, and can also be used for recording in the process of charging from a 220V network or portable chargers, which increases the battery life by 30-40 times.

Solar panel stuff

[solar_power_system_calc.txt](#)

- inverter?
- battery?
- solar panel?

1) load calculation

- assume 4x25w led light, 2x80w fan, 1x40w tube light, 1x50w tv
- total power = $100\text{w} + 160\text{w} + 40\text{w} + 50\text{w} = 350\text{w}$

2) inverter selection

- load = 350w (consider: 500w)
- recommended: 800w-1000w

3) battery selection

- assume 12v dc battery
- for 350w ac load, $i(\text{dc}) = 350\text{w}/12\text{v} = \sim 30\text{a}$
- assume battery operation of 8h
- battery capacity = $30\text{a} \times 8\text{h} = 240\text{ah}$

250ah battery available!

4) battery charging current calculation

- assume 250ah
- charging current = $\sim 10\%$ current rating (Ah)
- charging current = 25A

5) solar panel selection

- solar panel current = charging current + load current = $25 + 30 = 55\text{A}$
- solar panel power = $12\text{v} \times 55\text{A} = 660\text{W}$
- solar panel options: 125w / 180w / 375w / 440w

- solar panel count = $660W / 180W = \sim 4$!

From:

<http://azman.unimap.edu.my/dokuwiki/> - **Azman @UniMAP**

Permanent link:

<http://azman.unimap.edu.my/dokuwiki/doku.php?id=notes:misc&rev=1709879606>

Last update: **2024/03/08 14:33**

